

LINEAR INDUCTANCE

Small inductance made on ferrite cylinder

Inductance tolerance + - 10%

The codes with letter " V " are realize for vertical mounting but it is possible have for horizontal mounting with the code letter " O "

CODE	INDUCTANCE microHenry	CURRENT A	DIMENSION OPEN		
			A	B	C
IN0A1	10	1	4	17	13
IN0B1	5	3	5	17	15
IN0C1	8	1.5	4	17	13
IN0D1	10	1.5	4	17	13
INDE1	12	1.5	4	17	14
IN001	2	3	5	15	8.5
IN002	2	5	6	15	14
IN003	3	2	5	15	9
IN004V	3.5	8	7	15	5
IN005	10	1	5	15	13
IN006	82	1	6	15	6
IN007	90	1.1	6	15	7
IN008	4.7	5	6	20	13
IN009	4.7	4	6	20	14
IN010	8.5	1.5	5.5	20	16
IN011	33	2	6	20	8
IN012	70	3	7	20	18
IN013	100	1.5	7	20	18
IN014	140	1.5	7	20	18
IN015V	180	1	7	20	5
IN016	300	3	8	20	18
IN017	15	3	7	25	22
IN018V	18	5	8	25	7
IN019	16	0.7	6	20	15
IN020	16	1.5	6	20	15
IN021V	22	4	9	20	8
IN022V	25	7	10	20	8

